

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 0 704 985 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
03.04.1996 Bulletin 1996/14

(51) Int. Cl.⁶: H04B 1/707, H04B 7/005,
H04B 7/02

(21) Application number: 95112921.2

(22) Date of filing: 17.08.1995

(84) Designated Contracting States:
DE FR NL SE

• Krumpe, Alfred Michael
D-82229 Seefeld (DE)

(30) Priority: 28.09.1994 GB 9419496

(74) Representative: Allen, Derek
Siemens Group Services Limited
Intellectual Property Department
Roke Manor
Old Salisbury Lane
Romsey Hampshire SO51 0ZN (GB)

(71) Applicant: ROKE MANOR RESEARCH LIMITED
Romsey, Hampshire, SO51 0ZN (GB)

(72) Inventors:
• Hulbert, Anthony Peter
Shirley, Southampton SO15 5AN (GB)

(54) Clock phase adjustment circuit in a RAKE receiver for spread spectrum signals

(57) For a Rake Receiver in which the received signal is sampled at only one sample per chip, the signal is energy collected from several multipath components by the Rake fingers. If any multipath component is not perfectly aligned with the sampling time, several Rake fingers will be needed to collect its energy. If the number of Rake fingers available is limited then more efficient collection of energy is possible if fine timing correction is applied to the sampling so that optimum sampling is applied to the strongest multipath component. In this way only one Rake finger is required and the other Rake fingers may be dedicated to the remaining multipath components. The present invention uses two types of control methods, a Tau dither phase control circuit or a pilot jitter clock circuit. The control circuit generates control signals for the various Rake fingers and also controls a clock phase adjuster which in turn controls a sample and hold circuit which receives the analogue complex baseband input signal which is fed via a digital to analogue converter into a complex shift register, each stage of which is connected to each Rake finger and is selectable by each Rake finger.




Fig. 1

EP 0 704 985 A2

Description

The present invention relates to apparatus for use in equipment providing a digital radio link using direct sequence spread spectrum between a fixed and a mobile radio unit.

In co-pending patent application number 9316489.5, there is described a comprehensive Rake Receiver in which a contiguous set of Rake fingers is not required. The savings in cost and complexity are maximised if the fewest number of Rake fingers are used. The sampling of a received signal is performed at only one sample per chip and multiple Rake fingers are used.

The Rake fingers referred to above may be assigned to a single multipath component in order to acquire most of its energy when the component is sampled at a non optimum time. When the number of available Rake fingers is limited (eg n), these are assigned to the n strongest responses to the multipath components. If the strongest multipath component is non optimally sampled then several Rake fingers will need to be assigned to its responses in order to recover most of its power. In this case fewer Rake fingers remain available for assignment to the other multipath responses. If the timing of sampling can be held such that the strongest multipath component is always sampled optimally, then only one Rake finger will be needed for its reception. This makes available more of the other Rake fingers for combining the signal from the other multipath components, permitting improved overall performance. Conversely, for the same performance a smaller number of Rake fingers could be used.

In the context of CDMA cellular mobile radio systems, the present invention is only of benefit on the down-link (base station to mobile unit direction). The reason for this is that the base station receiver must handle signals received from many mobile units, all coming over different propagation paths so that the delays associated with the strongest path for every signal will be different. Since all signals pass through a single digital to analogue converter it is not possible to control the timing of the sampling for the different received signals independently.

For the mobile unit receiver, however, the signal is received from only one base station so that alignment is possible. The saving from this is most beneficial, because there are far more mobile unit receivers than base station receivers and because power consumption is critical.

Accordingly, an aim of the present invention is to provide apparatus in which a timing loop is closed around a single Rake finger which is experiencing the strongest signal, which is sampled at only one sample per chip thereby rendering arbitrary the timing of other Rake fingers with respect to their multipath components.

According to the present invention there is provided apparatus for use in equipment providing a digital radio link between a fixed and a mobile radio unit, said apparatus comprising a radio receiver having a plurality of Rake fingers, each Rake finger having means for selec-

tively receiving the contents of each bit of a shift register, said shift register being arranged to receive an analogue complex baseband signal via a sample and hold circuit and a digital to analogue converter, wherein said sample and hold circuit receives a control signal from a clock phase adjuster circuit which is controlled by control means in dependence upon an output signal received from each Rake finger.

An embodiment of the present invention will now be described with a reference to the accompanying drawings wherein:

Figure 1 shows a block diagram of a single finger aligned Rake receiver,

Figure 2 shows a block diagram of the controller shown in Figure 1, and

Figure 3 shows a block diagram of an alternative controller as shown in Figure 1.

Referring to Figure 1 there is shown a basic single finger aligned Rake finger comprising three Rake fingers 2, 4, 6. It will be appreciated that each Rake finger is identical and the description hereafter refers to the Rake finger 2 only. Each Rake finger comprises a selectable switch 8 the output of which is connected to an input of a pilot correlator 10 and to an input of a signal correlator 12. Each correlator generates an inphase output signal and a quadrature phase output signal. Each output from the pilot correlator 10 is connected to a filter 14, 16 respectively, the outputs of which are connected to first and second inputs of a multiplying circuit 18, 20 respectively and to an input of multiplying circuits 22, 24 respectively. The outputs of the signal correlator 12 are each connected to an input of a delay circuit 26, 28, the output of which is connected to a further input of a respective multiplying circuit 22, 24. The outputs from the multiplying circuits 18, 20 are connected to a summator 27, and the outputs of the multipliers 22, 24 are connected to a summator 30. The output summator 30 is connected via a controlled switch 32 to a further summator 34. The output of the summator circuit 27 is connected to an input of the control circuit 36. The output from the summator 30 and of the summators in the other Rake fingers are similarly connected to an input of the summator 34, the output of which generates the demodulated data. The outputs from the summators 27 in the other Rake fingers are also connected to the input of the control circuit 36. The output of the control circuit 36 is connected to an input of a clock phase adjuster circuit 38, the output of which controls a sample and hold circuit 40 which receives at an input thereof, an analogue baseband signal on input lead 42. The output of the sample and hold circuit is connected to a digital to analogue converter 44, the output of which is connected to a first stage of a complex shift register 46. Each stage of the complex shift register 46 is connected to a respective input of the selectable switch 8 in each Rake finger.

The control circuit 36 provides a signal to control the clock phase of the sample and hold circuit 40 via the

clock phase adjuster circuit 38 to obtain optimum sampling. The control can be performed in either a digital or an analogue fashion. The functionality of the control circuit 36 either implements a Tau dither loop (as familiar to those versed in the art) or a jittered pilot receiver as described in patent application number 9415191.7. The remainder of the circuit operation is as described in patent application number 9413268.5.

Referring to Figure 2, the control function implemented by a Tau Dither loop will now be described.

The control circuit comprises several integrators 50, 52, 54 which receive the output signals from the summators 27 in each Rake finger of Figure 1. These signals are also connected to a plurality of control switches 56, 58, 60. These switches are controlled by a largest select circuit 62 which receives the outputs from the integrator circuits 50, 52 and 54. The output of each switch 56, 58, 60 is connected to an input of an inverter 64 and to an input of a switching circuit 66 the function of which is to short circuit the inverter 64. The output of the subtractor circuit 64 is connected to a further input of the switch 66, the output of which is connected to an integrator filter 68. The output of the integrator filter 68 is connected to the input of a summator 70. The switch 66 and the further switch 72 are controlled by a dither clock generator 74. The switch 72 is arranged to switch a positive or negative offset to a further input of the summator 70, the output of which is used to control a clock phase and is applied to the clock phase adjuster 38 in Figure 1.

The integrators 50, 52, 54 average the signal power over a measured interval (several milliseconds) and the largest is selected and routed by the switches 56, 58, 60 to an inverter 64 and switch 66 which alternatively adds and subtracts the current measurement into the integrator 68. Synchronously with this operation, a Dither signal is generated and added to the output of the control signal. Operation is thus that the Dither signal causes the pilot power for the strongest Rake to be measured when the sample phase is early and when it is late. Alternate addition and subtraction of these into the integrator 68 is equivalent to feeding the difference of early and late measurements into the loop filter. When the timing is correct, the pilot signal in the early case will be the same as in the late case.

Referring to Figure 3, a pilot jitter solution is shown. In Figure 3 like elements as in Figure 2 have been given the same reference numeral and operate in the same manner. It will be noted that the difference is the provision of pilot jitter clock 76 which is used directly to control the switch 66. There is no need for a summator 70 as shown in Figure 2 or the additional switch 72 for providing a positive and negative offset. As mentioned above, there is no need for a Dither circuit since this is implemented on the pilot in the transmitter. The pilot jitter clock is synchronised to the local pilot code, dividing between the early and late phases of the pilot jitter.

It will readily be appreciated by those skilled in the art the various implementations are possible within the scope of the present invention.

Claims

1. Apparatus for use in equipment providing a digital radio link between a fixed and a mobile radio unit, said apparatus comprising a Rake receiver having a plurality of Rake fingers, each Rake finger having means for selectively receiving the contents of each bit of a shift register, said shift register being arranged to receive an analogue complex baseband signal, via a sample and hold circuit and a digital to analogue converter, wherein said sample and hold circuit receives a control signal from a clock phase adjuster circuit which is controlled by control means in dependence upon an output signal received from each Rake finger.
2. Apparatus as claimed in claim 1, wherein each Rake finger includes a pilot correlator from which said output signal is generated.
3. Apparatus as claimed in claim 1 or claim 2, wherein the control means is a Tau dither phase control circuit.
4. Apparatus as claimed in claim 1 or claim 2, wherein the control means is a pilot jitter phase control circuit.
5. Apparatus as claimed in claim 3, wherein the Tau dither control circuit includes integration means for averaging the signal power over an interval of time on each input line to the control means, means for selecting the largest signal, means for alternately adding and subtracting said selected signal into a further integrator, and means for adding a dither signal to the output signal of said further integrator.
6. Apparatus as claimed in claim 4, wherein the dither phase control circuit includes integration means for averaging the signal power over an interval of time on each input line to the control means, means for selecting the largest signal, and means for alternately adding and subtracting said selected signal into a further integrator under the control of a pilot jitter clock signal.




Fig. 1




Fig. 2




Fig. 3



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 704 985 A3

(12) **EUROPEAN PATENT APPLICATION**

(88) Date of publication A3:
05.04.2000 Bulletin 2000/14

(51) Int. Cl.⁷: H04B 1/707, H04B 7/005,
H04B 7/02

(43) Date of publication A2:
03.04.1996 Bulletin 1996/14

(21) Application number: 95112921.2

(22) Date of filing: 17.08.1995

(84) Designated Contracting States:
DE FR NL SE

(30) Priority: 28.09.1994 GB 9419496

(71) Applicant:
ROKE MANOR RESEARCH LIMITED
Romsey, Hampshire, SO51 0ZN (GB)

(72) Inventors:
• Hulbert, Anthony Peter
Shirley, Southampton SO15 5AN (GB)

• Krumpe, Alfred Michael
D-82229 Seefeld (DE)

(74) Representative: Allen, Derek
Siemens Group Services Limited,
Intellectual Property Department,
Siemens House,
Oldbury
Bracknell, Berkshire RG12 8FZ (GB)

(54) **Clock phase adjustment circuit in a RAKE receiver for spread spectrum signals**

(57) For a Rake Receiver in which the received signal is sampled at only one sample per chip, the signal is energy collected from several multipath components by the Rake fingers. If any multipath component is not perfectly aligned with the sampling time, several Rake fingers will be needed to collect its energy. If the number of Rake fingers available is limited then more efficient collection of energy is possible if fine timing correction is applied to the sampling so that optimum sampling is applied to the strongest multipath component. In this way only one Rake finger is required and the other Rake fingers may be dedicated to the remaining multipath components. The present invention uses two types of control methods, a Tau dither phase control circuit or a pilot jitter clock circuit. The control circuit generates control signals for the various Rake fingers and also controls a clock phase adjuster which in turn controls a sample and hold circuit which receives the analogue complex baseband input signal which is fed via a digital to analogue converter into a complex shift register, each stage of which is connected to each Rake finger and is selectable by each Rake finger.




Fig. 1

EP 0 704 985 A3



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 95 11 2921

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
A	WO 91 07036 A (QUALCOMM INC) 16 May 1991 (1991-05-16) * abstract * * page 7, line 30 - page 8, line 3 * * page 10, line 34 - page 11, line 5 * * page 11, line 21 - line 29 * * page 18, line 32 - page 19, line 10 * * claims 1,2,6 * ---	1-6	H04B1/707 H04B7/005 H04B7/02
A	GB 2 268 364 A (ROKE MANOR RESEARCH) 5 January 1994 (1994-01-05) * abstract * * page 4, line 5 - line 17 * ---	1-6	
A	EP 0 385 636 A (SPERRY MARINE INC) 5 September 1990 (1990-09-05) * abstract * * claim 1 * -----	1,3,5	
			TECHNICAL FIELDS SEARCHED (Int.Cl.6)
			H04B
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 8 February 2000	Examiner Ó Donnabháin, E
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

EPO FORM 1503 03/92 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 95 11 2921

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

08-02-2000

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
WO 9107036 A	16-05-1991	US	5109390 A	28-04-1992
		AT	163244 T	15-02-1998
		AU	649987 B	09-06-1994
		AU	6874891 A	31-05-1991
		CA	2072876 A	08-05-1991
		CN	1061311 A,B	20-05-1992
		DE	69032044 D	19-03-1998
		DE	69032044 T	10-06-1998
		EP	0500761 A	02-09-1992
		ES	2113353 T	01-05-1998
		FI	922082 A	07-05-1992
		GR	3026464 T	30-06-1998
		IL	96220 A	12-04-1994
		JP	4502844 T	21-05-1992
		MX	173030 B	28-01-1994
		NO	304207 B	09-11-1998
		SG	52745 A	28-09-1998

GB 2268364 A	05-01-1994	EP	0642243 A	08-03-1995

EP 0385636 A	05-09-1990	US	4965808 A	23-10-1990
		JP	2248881 A	04-10-1990

EPO FORM P0459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

This Page Blank (uspto)